# **Pro Tools Standard Matrix Profile Setup and Quick Start Guide**



#### Introduction

The first part of this tutorial details how to setup Pro Tools with your SSL Matrix. The second part details the commands assigned to this profile.

This tutorial assumes that you have already installed all the necessary Matrix related software on your computer and that there is both a working network and USB connection from your DAW computer to the Matrix. If you have yet to configure this part of your system please refer to the **Matrix 2 Owner's Manual** before continuing.


#### Installing the profile

The Pro Tools Standard profile is automatically installed when you update your Matrix console software to **V2.0/6**. In addition, it is recommended that you have the latest version of the Matrix remote application installed. Go to the SSL website > Matrix Product page > **Downloads** to make sure you are up-to-date.

## ipMIDI Setup

#### **Apple Macintosh OSX**

- 1) Close all applications using MIDI
- 2) Open AudioMidi Setup (MacintoshHD > Applications > Utilities > Audio MIDI Setup)
- Open the MIDI Window (Audio MIDI Setup > Window > Show MIDI Window)
- 4) Double click the ipMIDI icon
- 5) Set number of ports to 9 and ensure that 'Loopback' is **not ticked** and then press 'Apply'




#### OR

#### Microsoft Windows OS


This setup information covers Windows XP, Vista and Windows 7 and 8 (32+64-bit)

- 1) Launch the ipMIDI Monitor application (Start > Menu > Programs > ipMIDI)
- 2) Ensure Ports 1 to 9 are not muted
- 3) Un-tick 'Loop Back'
- 4) Set 'Ports after Reboot' to 9 and ensure that 'Loopback' is not ticked and then press 'OK'

Note: If you are opening up Ports for the first time, after Rebooting your computer, these will be 'muted'. Be sure to open ipMIDI back up and untick the muted Ports



## **Setting up Pro Tools**



#### **Device Setup**

Control surfaces are configured in the **Setup** > **Peripherals...** > **MIDI Controllers** menu. In this example we will setup Pro Tools for operation on DAW layer 1 of Matrix.

- 1) Setup the first HUI controller row to 'Receive From' and 'Send To' on ipMIDI Port 1, with '#Ch's' set to 8.
- 2) Setup the second HUI controller row to 'Receive From' and 'Send To' on ipMIDI Port 2, with '#Ch's' set to 8.


#### A note on Numeric Keypad Setup

Make sure that in Pro Tools **Preferences > Operation**, the Numeric Keypad is set to '**Transport**', as some of the shortcuts assigned to Matrix only work in this mode.

#### Matrix Setup

Go to the Matrix Remote application and ensure the selected profile for DAW 1 is 'Pro Tools Standard'.


## **Default**



Above you can see the assignments for Matrix' Default key set. You are in the Default Key Set when the User 1, User 2, User 3 or User 4 keys are not selected.

∢ Prev	Locates to previous marker	
Next >	Locates to next marker	
V-Pot	Opens the V-Pot menu	
I/O	Opens the I/O menu	
MemLoc	mLoc Opens/closes the Memory Locations window	
Big C	ig C Opens/closes the Big Counter window	
AutoEn	toEn Opens the AutoEn Menu	
AWind	ind Opens the Automation Window	
Edit	Brings the Edit window to the foreground	
Mix	Bring the Mix window to the foreground	
Sus G	s G Suspends/Suspends Groups	
Plugs	Plugs Shows/hides the Plug-In window of selected plug-in	
Trans	Trans Shows/hides transport window	
RecRdy	Record-ready for all tracks	
P Roll	Toggles Pre and Post Roll on/off	
Click	Toggles the metronome on/off	


## The V-Pot Submenu



The image above shows you the assignments for the V-Pot Submenu.

Pan	V-Pots control Pan levels (hold OPT modifier whilst moving to see value)	
Mute	Changes push function of V-Pots between Muting sends or Pre/Post	
Dfault	Default faders/pan positions. Press and hold whilst pressing a channel's SEL	
	key	
Assign	Enters/Exits the HUI Assign mode for Plug-ins and I/O assignments	
Send A	V-Pots control Send A levels	
Send B	V-Pots control Send B levels	
Send C	V-Pots control Send C levels	
Send D	V-Pots control Send D levels	


# The I/O Submenu



The image above shows the assignments for the I/O Submenu.

Assign	Enters/Exits the HUI Assign mode for Plug-ins and I/O assignments	
Input	Allows assign mode to set channel inputs	
Output	Allows assign mode to set channel outputs	
	Unassigned	


## The AutoEn Submenu



The image above shows the assignments for the AutoEn Submenu.

Fader	Enables/disables Fader automation	
Mute	Enables/disables Mute automation	
Pan	Enables/disables Pan automation	
Send	Enables/disables Send automation	
SMute	Enables/disables Send Mute automation	
Plugin	Enables/disables Plugin automation	
AutoS	Enables/disables all automation	
	Unassigned	


## User 1



The image above shows the assignments for User 1.

Tabs to previous transient (providing Tab To Transient is enabled)	
Tabs to next transient (providing Tab To Transient is enabled)	
Tabs to next transient and also highlights area (providing Tab To Transient is	
enabled)	
Vertical Zoom Out for all tracks	
Vertical Zoom In for all tracks	
Cut highlighted region	
Cycles selection of Pro Tools' edit modes – Shuffle, Spot, Slip and Grid	
Cycles selection of Pro Tools' editing tools	
Brings the Edit window to the foreground	
Bring the Mix window to the foreground	
Enables/disables Tab To Transient	
Selects all regions on track	
Separates region at playhead	
Copy highlighted region	
Paste highlighted region	
Toggles the metronome on/off	


## User 2



The image above shows the layout for User 2.

Intro	Enters a marker that names itself to 'INTRO'	
Verse	Enters a marker that names itself to 'VERSE'	
Chorus	Enters a marker that names itself to 'CHORUS'	
Mid8	Enters a marker that names itself to 'MIDDLE 8	
BrkDwn	Enters a marker that names itself to 'OUTRO'	
Outro	Enters a marker that names itself to 'MID 8'	
MemLoc	Opens/closes the Memory Locations window	
Delete	Deletes the last entered Memory Location(s)	
	Unassigned	


# User 3



The image above shows the assignments for User 3.

Drums	Opens/closes the Drum Names Submenu	
Bass	Opens/closes the Bass Names Submenu	
Keys	Opens/closes the Keys Names Submenu	
Guitar	Guitar Opens/closes the Guitar Names Submenu	
String	Opens/closes the Strings Names Submenu	
Vocals	<b>/ocals</b> Opens/closes the Vocals Names Submenu	
Perc	Opens/closes the Percussion Names Submenu	
FX	Opens/closes the FX Names Submenu	
	Unassigned	


## **Drum Names Submenu**



The image above shows the assignments for the Drum Names Submenu.

Kick	Types in the name 'KICK' followed by enter. Double tap 'SEL' key to enter	
	name dialogue before pressing this.	
Snr T	Types in the name 'SNR T' followed by enter. Double tap 'SEL' key to enter	
	name dialogue before pressing this.	
Snr B	Types in the name 'SNR B' followed by enter. Double tap 'SEL' key to enter	
	name dialogue before pressing this.	
Tom 1	Types in the name 'TOM 1' followed by enter. Double tap 'SEL' key to enter	
	name dialogue before pressing this.	
Tom 2	Types in the name 'TOM 2' followed by enter. Double tap 'SEL' key to	
	enter name dialogue before pressing this.	
Hats	Types in the name 'HATS' followed by enter. Double tap 'SEL' key to ente	
	name dialogue before pressing this.	
OHS	Types in the name 'ROOMS' followed by enter. Double tap 'SEL' key to	
	enter name dialogue before pressing this.	
Room	Types in the name 'ROOMS' followed by enter. Double tap 'SEL' key to	
	enter name dialogue before pressing this.	

# **Transport / Utilities**



The image above shows the assignments for the Matrix's transport/utilities section.

PlayFS	Play command is assigned to first footswitch connection	
RecFS	Record command is assigned to second footswitch connection	
Shift	Shift command (HUI)	
Ctrl	Ctrl command (HUI)	
Alt	Alt command (HUI)	
Option	Option command (HUI)	
Enter	Enters a marker	
F8	Cycles Pro Tools edit tools	
Save	Saves session	
Undo	Undo	
Previous	Locates to previous marker	
RTZ	Locates to session start	
Next	Locates to next marker	
End	Locates to region end	
Last	Locates to last locator	
Loop	Turns loop playback on/off	
Nudge -	Nudge left by Nudge value	
Nudge +	Nudge right by Nudge value	
Online	Toggles Online Sync on/off	
Q Punch	Toggles Quick Punch record on/off	

## **List of HUI Functions**

The Pro Tools profile contains a mixture of HUI commands and USB keyboard shortcuts. To help you see how we have renamed the commands, see the table below.

BLACK TEXT = HUI command RED TEXT = USB keyboard shortcut

DAW CMD / KEYBOARD SHORTCUT	SOFTKEY LABEL (RE-NAMED)
Prev Marker	∢ Prev
Next Marker	Next >
	V-Pot (Menu)
	I/O (Menu)
Apple+Numeric keypad 5	MemLoc
Apple+Numeric keypad 3	Big C
	AutoEn (Menu)
Apple+Numeric keypad 4	AWind
Edit to foreground	Edit
Mix to foreground	Mix
Shift+Apple+G	Sus G
Open/close plugin editor	Plugs
Open/close transport	Trans
Rec/Rdy all	RecRdy
Apple+K	P Roll
Numeric keypad 7	Click
Pan	Pan
Mute	Mute
Default	Dfault
Assign	Assign
Send A	Send A
Send B	Send B
Send C	Send C
Send D	Send D
Input	Input

,	Output
Auto Enable Fader	
	Fader
Auto Enable Pan	Mute
Auto Enable Send	Pan
Auto Enable Send Mute	Send
Auto Enable Plugin	SMute
Auto Enable Plugin	Plugin
Auto Suspend	AutoS
Alt+Tab	< Tab
Tab	Tab >
Shift+Tab	SelTab
Ctrl+Alt+Down Arrow	Z Out
Ctrl+Alt+Up Arrow	Z In
Apple+X	Cut
Edit Mode	EdMode
Edit Tool	EdTool
Alt+Apple+Tab	Tab T
Apple+A	Sel R
Apple+E	Split
Apple+C	Copy
Apple+Y	Paste
Numeric Enter + 'INTRO' + Enter	Intro
Numeric Enter + 'VERSE' + Enter	Verse
Numeric Enter + 'CHORUS' + Enter	Chorus
Numeric Enter + 'MID 8' + Enter	Mid 8
Numeric Enter + 'BREAKDOWN' +	BrkDwn
Enter	
Numeric Enter + 'OUTRO' + Enter	Outro
Apple+Z	Delete
Shift/All	Shift
Option/All	Option
Control	Ctrl
CMD/Alt/Fine	Alt
Fkey8/Esc	Esc
Play Foot Switch	PlayFS
Record Foot Switch	RecFS
RTZ	RTZ

#### Document Version 1.0

End	End
Last Marker	Last
Loop	Loop
KPad +	Nudge -
KPad -	Nudge +
On-line	Online
Quick Punch	QPunch
Save	Save
Undo	Undo
Rewind	Rewind
Forward	Forward
Stop	Stop
Play	Play
Record	Record